

V1.4

BESTEK

Welcome Guide

8-Outlet Smart Individual Control Power Strip

MODEL NO.: MRJ8005

BESTEK GLOBAL LLC
1290E ELM ST, #A-8, ONTARIO,
CA91761
COMPANY: BESTEK
PHONE: 909-816-0181

8-Outlet Smart Individual Control Power Strip

Do you really think the devices that you turn off draw no power? Though you don't use it, it still draws power which is been called a "phantom load". The best way to avoid its happening is to cut off the power from the power strip.

Our Solution

MODE 1: Smart Control Mode (Switch the red button to Off/Ctrl position)

BESTEK Smart Individual Control Power Strip features 1 control outlet. This outlet senses when your computer or whichever device is plugged in to the outlet is turned off/on. Peripheral devices plugged into some or all of the remaining outlets with switches on the "Ctrl" position are automatically powered up/down whenever you switch on/off the main device.

If you want to use some of the outlets to power separate devices/appliances not connected to the devices plugged into the control outlet, simple make sure the switch is on the "Always on" position.

MODE 2: Individual Control Mode

When the control outlet is not in use, the red switches act as standard "Off/On" switches so you can turn on or off your devices separately!

Note

- Under "Smart Control Mode": when the output of control outlet is more than 20W, the smart outlets will be activated. When the output of control outlet is less than 15W, the power of the smart outlets will be cut off.

Other Features

- * 7 "Smart Outlets" with their own Off/Ctrl & Always ON button and 1 "Control Outlet", allow you to easily turn off devices that are not in use without unplugging it.
- * 2 USB charging ports with Smart IC technology can automatically identify your device to deliver its fastest possible charging speed up to 2.4 amps per port/4.2 amps total, integrated green LED to show its working status.
- * 6.6-foot long 14-gauge heavy-duty power cord delivers optimal, safe AC power to your devices. Keyhole slots on the back for installation in a wide variety of applications.
- * Red LED power switch with an integrated 15 amp circuit breaker prevent damage to your devices. Built-in over-heated, overload, over-charging protection against short circuits.

Specification

Input/Output	100-125V~ 60Hz 15A 1875W MAX
USB Output	USB: 5V=0-2.4A Total 2xUSB Output: 4.2A 21W MAX
Sockets	8US Standard AC Outlets + 2USB Port
Working Environment	temperature: -5 C ~ 40 C; humidity: 10% ~ 90%RH
Storage Environment	temperature: -20 C ~ 80 C; humidity: 5 ~ 95%RH
Cord Length	1.8m (Customized is available)
Dimensions	15.27*3.02*1.60 inch

Here is an example:

You can plug your computer in the "Control Outlet", then plug other devices such as Speaker, Monitor, Printer in another 3 "Smart Outlets" and switch these 3 outlets to the "Off/Ctrl" position. Then, when you turn on/off the computer, the 3 outlets will power on/off automatically.

If you also have a desk lamp and want the lamp stay powered, you can switch the button to "Always on" position. Then it will never shut down.

Or, you can leave the "Control Outlet" unused, and plug these 3 devices into the other 7 "Smart Outlets". In this way, the red button is simply "On/Off" button.

Package Contents

- * BESTEK 8-Outlet Surge Protector
- * Welcome Guide

Warranty

Our company provides customers with a warranty of 18 MONTHS from the date of purchase.

Contact US

For any inquiries or comments concerning our products, please send an email to us and we will respond to you as soon as possible. If there is any quality-related issue with the product, you may request a REPLACEMENT OR REFUND by submitting a request to us.

ATTENTION ⚠

Pour réduire le risque de choc électrique, Pour Usage À L'intérieur
Seulement. Risque de choc électrique. Ne pas brancher
dans une autre source de courant portative.
EMPLOYER UNIQUEMENT DANS DES EMPLACEMENTS SECS
Utilisation uniquement pour le matériel informatique

CAUTION ⚠

TO REDUCE THE RISK OF ELECTRIC SHOCK, USE ONLY INDOORS
RISK OF ELECTRIC SHOCK. DO NOT PLUG INTO ANOTHER
RELOCATABLE POWER TAPS
USE ONLY IN DRY LOCATION
ONLY FOR IT EQUIPMENT USE

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

MADE IN CHINA

