

BESTEK
BESTEK ELECTRONIC LTD

Access House, 141 Morden Road
Mitcham
London CR4 4DG
United Kingdom
TEL:02086481668

150 Watt POWER INVERTER

MODEL NO.: MRI1513U-UK PLUG STYLE

Introduction:

The power inverter DC-AC 150W with Dual USB charging port is designed for all major brand notebook computers, digital portables like video camcorder, digital camera, DVD player, etc., its AC outlet operates like your house main sockets.

Before You Begin

- Use it only after reading all the instructions.
- It's normal for the inverter to become warm to the touch while you are using it, avoid placing the inverter in direct sunlight or next to heat-sensitive materials.

Safety Precautions

- X Do not use with any appliance with dangerous voltage warning.
- X Do not use with over 16V DC input.
- ! Make sure to provide adequate ventilation to the inverter.
- X Never place inverter in an enclosure or near a heat source such as heat vent of cars and in direct sunlight.
- X Do not use the inverter near any flammable liquid or gases.
- X Do not expose to liquid or moisture or humidity.
- X Do not handle with wet hands.
- ! This inverter's working temperature is -10°C-40°C
- X Do not put metal fragment (eg. such as wire) inside.
- X Do not attempt to disassemble.
- ! Keep out of the reach of children.



Technical Specifications

Input voltage range	DC 11-15V
Output rated power	150Watts continuous, 180Watts max.
Output voltage&frequency	AC 220-240V/50Hz
Output voltage for USB charging port	DC 5V/2.1A (Rated) 3.1A max
Indicator	Dual color LED(Green/operation, Red/shutdown)
Protections	Short circuit, overload, over temperature, low battery voltage, over battery voltage
Over voltage shutdown	DC15-16V
Low voltage shutdown	DC10-10.5V

Operation Guide

- Make sure that the vehicle's cigarette lighter socket is workable and available.
- Plug in the inverter into the vehicle's cigarette lighter socket.
- The green LED should light up and inverter is ready for use.
- Connect the plug of your electrical device to the inverter's AC socket.
- Please remove the inverter from the cigarette lighter socket when not in use.

LED Indicator

No light from LED	No power to inverter
Constant Green	Power on and in operation
Constant Red	Inverter shutdown

Attention:

For DC 12V use only, can not be applied to DC 24V

MADE IN CHINA